

Manual Switches

Electronic Control Pushbutton

AML21 Series

INCANDESCENT OR NON-LIGHTED DISPLAY

Electrical Data	page 19
Buttons	page 43
Lamps and LEDs	page 58
Accessories	pages 56, 57
Mounting Dimensions	pages 59, 62



Buttons ordered separately.

- FEATURES**
- 1, 2, or 4 poles.
 - Silver or gold contacts.
 - Full guard bezel option.
 - Momentary or 2-level alternate action (push-on, push-off).
 - UL recognized, CSA certified.
 - Lamps can be furnished installed or ordered separately.
 - Lamp circuit independent of switch circuit.



AML21 ORDER GUIDE

AML21 B	B	A	2	AA									
Housing Type	Bezel Color	Incandescent Lamp Type	Terminal Type	Circuitry Codes (Each pole has double-throw)									
<p>Standard Bezel:</p> <p>AML21B Square Non-Lighted AML21C Square 1 Lamp Ckt. AML21E Rect. Non-Lighted AML21F Rect. 1 Lamp Ckt. AML21G Rect. 2 Lamp Ckts.</p> <p>Full Guard Bezel:</p> <p>AML21H Square Non-Lighted AML21J Square 1 Lamp Ckt. AML21K Rect. Non-Lighted AML21L Rect. 1 Lamp Ckt. AML21M Rect. 2 Lamp Ckts.</p>	<p>B Black</p>	<p>A No Lamp Installed</p> <p>B 6 V Lamp*</p> <p>C 14 V Lamp*</p> <p>E 28 V Lamp*</p>	<p>2 .110 × .020 (Solder or Quick-Connect)</p> <p>3 .025 × .025 (Printed Ckt. or Push-On)</p>	<table border="1" style="width: 100%;"> <tr> <td rowspan="2" style="text-align: center;">Silver Contacts</td> <td style="text-align: center;">Mom. Action AA 1-Pole AC 2-Pole CC 4-Pole</td> </tr> <tr> <td style="text-align: center;">Alt. Action AB 1-Pole AD 2-Pole CD 4-Pole</td> </tr> <tr> <td rowspan="3" style="text-align: center;">Gold Contacts</td> <td style="text-align: center;">Mom. Action BA 1-Pole BC 2-Pole DC 4-Pole</td> </tr> <tr> <td style="text-align: center;">Alt. Action BB 1-Pole BD 2-Pole DD 4-Pole</td> </tr> <tr> <td style="text-align: center;">Mom. Action EA 1-Pole EC 2-Pole</td> </tr> <tr> <td rowspan="2" style="text-align: center;">Gold-Plated Silver Contacts</td> <td style="text-align: center;">Alt. Action EB 1-Pole ED 2-Pole</td> </tr> </table>	Silver Contacts	Mom. Action AA 1-Pole AC 2-Pole CC 4-Pole	Alt. Action AB 1-Pole AD 2-Pole CD 4-Pole	Gold Contacts	Mom. Action BA 1-Pole BC 2-Pole DC 4-Pole	Alt. Action BB 1-Pole BD 2-Pole DD 4-Pole	Mom. Action EA 1-Pole EC 2-Pole	Gold-Plated Silver Contacts	Alt. Action EB 1-Pole ED 2-Pole
Silver Contacts	Mom. Action AA 1-Pole AC 2-Pole CC 4-Pole												
	Alt. Action AB 1-Pole AD 2-Pole CD 4-Pole												
Gold Contacts	Mom. Action BA 1-Pole BC 2-Pole DC 4-Pole												
	Alt. Action BB 1-Pole BD 2-Pole DD 4-Pole												
	Mom. Action EA 1-Pole EC 2-Pole												
Gold-Plated Silver Contacts	Alt. Action EB 1-Pole ED 2-Pole												

* Lamps will be installed per each lamp circuit specified in the Housing Type.

Example: **AML21BBA2AA**
 Square pushbutton switch housing non-lighted; black bezel; .110 × .020 termination; momentary action; 1-pole, double-throw; silver contacts.